

### Ready to Go with What You Can Rely On

# **Defense Series GL7 Tactical Flashlight User Manual**

### **Features**

- 1. Aluminum body with hard anodization
- 2. Luminus® SST-40 cool white LED boosts up to 2000 lumens\*
- 3. Deep and smooth CNC machined reflector, beam distance up to 280 meters
- 4. Uses 18650 Li-ion battery (3400mAh battery included)
- 5. Dual switch for EDC daily use and tactical/emergency
- 6. USB-C quick charge in 2 hours
- 7. 25.4mm/1" body fits standard weapon mount
- 8. IPX8 waterproof

Size: 144.5mm / 5.69" (Length) \* 25.4mm / 1" (Diameter)

Weight: 170g / 6.0oz (Battery, Battery Tube, Pocket Clip, and Tactical Ring included)

### **Operation**

- I. Side switch (Daily use)
- 1. Turn on: rapid double-click
- 2. Change mode: when it's turned on, click to cycle through Low-Medium-High-Turbo
- 3. Turn off: Press and hold for 0.3 seconds
- 4. Ramping: from off, press and hold the button to adjust the brightness from 10-1500 lumens and release to select the brightness, click to turn off.
- 5. Memory: It will go back to the last-used mode when turn on next time.
- \* It will stepdown to 800 lumens in 3 minutes when it works at Turbo mode due to the massive heat generated.

#### NOTE:

- 1. When the light was turned on by the side switch, a Half press or Full press the tail switch will go to Strobe mode, then Release or Full press the tail switch again will go back to the Daily Use mode.
- 2. If the light works over 1 minute, Click the side switch, Half press the tail then release or Full press then full press again will turn off the light.
- II. Tail switch (Tactical & Emergency)

### A. From off

- 1. Momentary on:
  - Half press to switch between Strobe SOS High, release to turn off or Full press to select the mode for constant on.
  - Memory: to set the default mode of the first half press/full press, just leave the mode working for over 3 seconds.
  - c. Turn off: Full press

B. From on

Half press or Full press: Strobe From strobe: Full press to turn off

### **Battery & Recharge**

### Before the first use, please remove the insulation sheet and fully charge the light.

- Included battery: 18650 3400mAh @max 10C discharge
  \*Compatible standard 18650 batteries but the output (brightness) may vary.
- b) Max runtime: 110 hours
- c) Recharge: USB-C
- d) Charge: 5V/3A, fully charged in 2 hours
- e) Charging indicator: Breathing green while in charge, and solid green once fully charged
- f) Low battery: 2.8V, the indicator will come on red to remind.








# Ready to Go with What You Can Rely On

## **Specifications**

	Low	Medium	High	Turbo	Strobe/SOS
Output	10lm	100lm	800lm	2000lm	1
Runtime	110 Hours	20 Hours	2.5 Hours	3Mins* + 2 Hours	1
Intensity	19000cd (max)				
Beam Distance	280m (max)				
Impact resistance	1.5m				
Waterproof*	IPX8				

- 1. Parameters may vary from environment, battery, using method, and flashlight.
- 2. To get best performance please use the original battery that comes with the flashlight.
- 3. \*Stepdown to 800 lumens in 3 minutes
- 4. \* The waterproof performance will get weaker by time as the O-rings aged.

# **Graphic of Turbo mode**



The runtime tested until the output stepdown to 1 lumen.

# **Packaging Content**

- a) GL7 Flashlight x1
- b) 3400mAh Li-ion battery x1 (Pre-install in the flashlight)
- c) Battery tube x1(Pre-install in the flashlight)
- d) Pocket clip x1 (Attached on the flashlight)
- e) Tactical ring x1 (Attached on the flashlight)
- f) USB-C charging cable x1
- g) Lanyard x1
- h) Extra charging port cover x1
- i) Extra O-ring x1
- j) User manual x1
- k) Warranty card x1



